

## FREQUENCY:

60 Hz

#### STANDARD SECONDARY VOLTAGE:

120 Volts

### INSULATION LEVEL:

600 Volts. 10 kV BIL. full wave

#### ACCURACY CLASS:

0.6 W, 1.2 X at 60 Hz

#### THERMAL RATING:

150 VA AT 30°C. amb., 100 VA AT 55°C. amb.

### APPROXIMATE WEIGHT:

7.75 lbs.

#### CONNECTIONS:

-Terminals are brass studs No. 10-32 with one lockwasher, flat washer, and regular nut

# **Voltage Transformer**



| Model  | 465  |
|--------|------|
| Width  | 3.63 |
| Height | 4.25 |
| Depth  | 3.75 |

# Model 465 rev 02222024

## **CERTIFICATIONS:**







| MODEL 465                     |
|-------------------------------|
| Approximate weight: 7.75 lbs. |

|                | • |             |                          |
|----------------|---|-------------|--------------------------|
| CATALOG NUMBER | VOLTAGE RATING                          | TURNS RATIO | REC. PRIMARY FUSE RATING |
| NOT FUSED      | VOLTAGE KATING                          | TURNS KATIO | REC. PRIMART FUSE RATING |
| 465-069        | 69.3:120                                | 0.58:1      | 5                        |
| 465-120        | 120:120                                 | 1:1         | 4                        |
| 465-208        | 208:120                                 | 1.73:1      | 2                        |
| 465-240        | 240:120                                 | 2:1         | 2                        |
| 465-277        | 277:120                                 | 2.31:1      | 2                        |
| 465-288        | 288:120                                 | 2.4:1       | 1.5                      |
| 465-300        | 300:120                                 | 2.5:1       | 1.5                      |
| 465-346        | 346:120                                 | 2.88:1      | 1.5                      |
| 465-480*       | 480:120                                 | 4:1         | 1                        |
| 465-600*       | 600:120                                 | 5:1         | 0.75                     |

- Each transformer has two plastic terminal covers.
- The core and coil assembly is encased in a thermoplastic shell and filled with resin.
- These transformers are designed for operation line to line. They may also be operated line to ground or line to neutral at reduced voltage (58% of rated volts).
- It is desirable to use a 1.6 amp fuse in the secondary to protect the transformer.
- With two exceptions these transformers are ANSI C57.13 group 1. Those marked \* are group 2.
- Models designed specifically for 50 Hz operation are avaliable with reduced performance consult factory for details.

